

5. Reliability Testing

The purpose of reliability testing is to ensure that products are properly designed and assembled by subjecting them to stress conditions that accelerate potential failure mechanisms. Reliability test methods are defined in many industrial standards, such as MIL-STD-883, the main source of the methods applied in reliability testing at Winbond. In this report, reliability tests have been divided into three categories: process-related reliability tests, package-related reliability tests, and device reliability tests.

Process-Related Reliability Tests

Dynamic Early Fail Study (EFR)

The purpose of the dynamic early fail study (EFR) is to estimate the infant mortality failure rate that occurs within the first year of normal device operation by accelerating infant mortality failure mechanisms. Typical stress temperature is set to 125 °C at nominal voltage (6.5 V for 5V SRAM and EPROM; 4.3 V for 3.3V SRAM; 4.6 V for 3.3V DRAM). The duration is 72 hours.

High-Temperature Operating Life Test (HTOL) (MIL-STD-883; 1005)

The purpose of the high-temperature operating life (HTOL) test is to determine the reliability of Products by accelerating thermally activated failure mechanisms by subjecting samples to extreme temperatures under biased operating conditions. The test is used to predict long-term failure rates in terms of FITs (failures in time), with one FIT representing one failure in 10^9 device hours. All test samples are screened directly after final electrical testing. The oven temperature for the HTOL test is 125 °C. Testing is performed with dynamic signals applied to the device, and the typical Vcc is the maximum operating voltage.

High-Temperature Storage Life Test (HTSL) (MIL-STD-883; 1008)

The high-temperature storage life test measures device resistance to a high-temperature environment that simulates a storage environment. The stress temperature is set to 150°C or 125°C to accelerate the effect of temperature on the test samples. In the test, no voltage bias is applied to the devices

Bias Life Test (BLT)

(MIL-STD-883; 1005.8 and
EIAJ-ED4701-D323)

Bias life test is to detect possible defects on passivation (contamination, surface inversion, un-stable characteristics of film), PN junction (junction degradation), oxide film (mobile ions, interface states), and bonding (open moralization, bonding defect). The test temperature is 125 °C and the duration is 1000 hours. The pins of the devices are combination biased.

Electrostatic Discharge (ESD) Test

The electrostatic discharge test measures the sensitivity of each device pin to electrostatic discharges that might occur during handling. At Winbond, ESD is evaluated by using the human body model (MIL-STD-883, Method 3015) with $C = 100 \text{ pF}$ and $R = 1.5 \text{ K}$ to simulate discharge through human contact.

Latch-Up Test

The latch-up test is a special test used with CMOS processes to detect parasitic bipolar circuits that can short the power and ground nodes when they are activated. Winbond adopts JEDEC-JC-78 standards: The current is applied to each I/O pin in steps while the power supply current is monitored. The current into the test pin must rise to a minimum of 100 mA without latch-up occurring.

Package-Related Reliability Tests

Preconditioning

The purpose of preconditioning is to measure the resistance of surface mount devices to the storage environment at the customer site and to thermal stress created by IR reflow or vapor phase reflow. Before they undergo the temperature-humidity-bias test, the temperature cycle test, the thermal shock test, the pressure cooker test or the highly-accelerated temperature and humidity stress test, surface mount devices are subjected to preconditioning and must then pass a final electrical test. The steps of precondition for SRAM, non-volatile and logic:

Step1: Temperature Cycle Test (-65 °C /150 °C),
5 cycles.

Step 2: Bake for 24 hours at 125 °C.

Step 3: Soak for 192 hours at 30 °C/RH60%.
(JEDEC LEVEL III)

Step 4: Execute VPR (215 °C, 60 Sec. Peak) or
IR Reflow, 3 passes .

DRAM :

Step1: Temperature Cycle Test (-65 °C /150 °C),
25 cycles.

Step 2: Bake for 20 hours at 125 °C.

Step 3: Soak for 168 hours at 85 °C/RH60%.
(JEDEC LEVEL II)

Step 4: Execute IR Reflow, 4 passes .

Temperature-Humidity-Bias Test (THB)

(EIAJ-IC-121-17)

The temperature-humidity-bias test is an environmental test designed to measure the corrosion and moisture resistance of plastic-encapsulated circuits. A nominal reverse bias is applied to the device to create electrolytic cells necessary to accelerate corrosion of the metallization or bond pads without heating the device. The duration of the test is 1000 hours, with readouts (final electrical tests) at 168 hours and 500 hours during the test. The stress temperature is 85 °C, and the humidity is RH 85%. The bias is the maximum operating voltage. Samples of surface mount devices must undergo preconditioning and pass a final electrical test prior the THB test

Temperature Cycle Test (TCT)

(MIL-STD-883; 1010)

The purpose of temperature cycle testing is to study the effect of thermal expansion mismatch among the different components within a specific die and packaging system. The cycling test system has a cold dwell at – 65 or –55 °C (LCD driver) and a hot dwell at 150 or 125 °C (LCD driver), and it employs a circulating air environment to ensure rapid stabilization at a specified temperature. During temperature cycle testing, devices are inserted into the cycling test system and held at cold dwell for 15 minutes, and then the devices are heated to hot dwell for 15 minutes. One cycle includes the duration at both extreme

temperatures and the two transition times. The transition period is less than one minute at 25 °C. The test duration is 200 cycles for SRAM, non-volatile, and logic, 300 cycles for LCD driver and 500 cycles for DRAM. Samples of surface mount devices must first undergo preconditioning and pass a final electrical test prior to the temperature cycle test.

Thermal Shock Test (TST)

(MIL-STD-883; 1011)

Thermal shock testing is similar to temperature cycle testing, except that in thermal shock tests an additional stress is provided: a sudden change in temperature due to a rapid transfer time. Thus the test can detect failure mechanisms caused by temperature transients and temperature gradients. The cycling test system has one fluorocarbon bath at –65 or –55 °C (LCD driver) and the other fluorocarbon bath at 150 or 125 °C (LCD driver). During thermal shock testing, devices are inserted into the cycling test system and held at cold dwell for 5 minutes and then heated to hot dwell for 5 minutes. One cycle includes the duration at both extreme temperatures and the two transition times. The transition period is less than 10 seconds at 25 °C. The test duration is 100 cycles. Samples of surface mount devices must undergo preconditioning and pass a final electrical test prior to the thermal shock test.

Pressure Cooker Test (PCT)

(EIAJ-IC-121-18)

The pressure cooker test is an environmental test that measures device resistance to moisture penetration and the effect of galvanic corrosion. The stress conditions for the pressure cooker test employed at Winbond are 121 °C (for SRAM, non-volatile and logic) and 127 °C (for DRAM), and 100% relative humidity. The duration of the test is 168 hours. Samples of surface mount devices are subjected to preconditioning and a final electrical test prior to the pressure cooker test. After the pressure cooker test, the leads of the test samples are cleaned and then baked at 150 °C for 1 hour before the final electrical test.

Highly-Accelerated Temperature and Humidity Stress Test (HAST) (JESD22-A110)

The highly accelerated temperature and humidity stress test is performed for the purpose of evaluating the reliability of non-hermetic packaged solid-state device in an environment with high humidity. It employs severe condition of temperature, humidity, and bias, which accelerate the penetration of moisture through the external protective material (encapsulated or seal) or along the interface between the external protective material and the metallic conductor, which pass through it. Samples of surface mount devices are subjected to preconditioning and a final electrical test prior to the highly-accelerated temperature

and humidity stress test. The stress conditions of the HAST test employed at Winbond are 130 °C, 85% RH, 2 atm and Vdd = maximum operating voltage and pin combination bias. The duration of the test is 168 hours for SRAM, non-volatile, and logic and 300 hours for DRAM.

Device Reliability Tests

Electromigration (EM) Test

Electromigration is the motion of interconnect metallization due to momentum exchange from the electron current. A convergence of metallic ion flux can lead to hillock formation, which may result in short circuits to adjacent or overlaying conductors. A divergence of the metallic ion flux can lead to void formation, which may result in open circuit failure. In the electromigration test, specially designed test structures are stressed by high-current densities and high temperature to accelerate the electromigration process. The stress temperature is 175 °C for the SRAM, LOGIC and EPROM process and 250 °C for DRAM process, respectively. The stress current density is about 10^6 Amp/cm². A test sample is defined as a failure if its resistance variation is more than 10% of its initial resistance. Regression analysis is used to find the best fit of lognormal distribution data so as to calculate the

median time-to-failure(MTF) under the stress

conditions. Then, by multiplying the temperature and current acceleration factors, we can find the MTF due to electromigration under use condition. Lifetime() is specified as $0.1\% \geq 100K$ hours @130°C for SRAM, LOGIC, EPROM process and $1ppm \geq 10$ year @85°C for the DRAM process.

Stress Migration (SM) Test

The test is performed for DRAM process only. The purpose of the test is to see if the stress cause inadmissible resistance variation. The stress temperature is 225°C and the criterion is specified as $\Delta R < 10\%$ after 1000Hrs stress.

Bias Temperature(BT) Test

The test is performed for DRAM process only. The purpose of the test is to investigate the degradation during the bias temperature stress due to ionic contamination or increased positive charge. The stress condition for it is +/-3.75V @ 140°C and the criterion is specified as $\Delta V_{th} < 50mV$ after 100Hrs stress.

Hot Carrier Effect (HCE) Test

Hot carrier effects occur in most transistors when the lateral electric field in the drain depletion region or in the channel becomes so large that the major carriers in the channel gain energy from the electric field faster. These carriers may gain enough energy (1.5 eV) to impact-ionize and create hole-electron pairs, which results in a measurable substrate current consisting of carriers with opposite charge to the major carriers in the channel. If the hot carriers further gain enough energy (3-4 eV), they can overcome the Si-SiO₂ barrier and be injected into the oxide layer. In the HCE test, the test MOS transistors are divided into three groups, which are DC-stressed under three different values of Vd higher than the maximum operating voltage. Three different values of Vd before Id becomes infinity as Vd increases are chosen as the three stress voltages. The gates of the test transistors are biased at the value such that Isub is the maximum value in Isub vs. Vg for NFET and the maximum value in Ig vs. Vg for PFET, respectively. The stress temperature is room temperature. A test sample is defined as a failure if the variation in I_{dsat} is more than 10% of its initial value for NFET, or the variation in Vth is more than 50mV for PFET. The lifetime is specified as $DC \geq 0.2$ year for SRAM, LOGIC, EPROM process and $AC \geq 10$ year for DRAM process, respectively.

Charge to Breakdown (QBD) Test

The purpose of the QBD test is to measure the breakdown charge density of the gate oxide. In the test, a constant current density is applied to a test sample until it breaks down. The stress current density is 0.1 Amp/cm^2 . To pass the test, the breakdown charge density of a test sample must be larger than 1 Coul/cm^2 at weibull 63%.

EBD Test

In the EBD test, the breakdown electric field of the gate oxide is measured by applying stepwise voltages to a test sample until it breaks down. The voltage step is 0.5 V/step . To pass the test, the breakdown electric field of a test sample must be larger than 8 MV/cm .

TDDB Test

The oxide will only allow a finite amount of charge to pass it before it breakdown. The purpose of TDDB testing is to characterize when this breakdown occurs and to evaluate oxide lifetime. Regression analysis is used to find the best fit of Weibull distribution data so as to calculate the median time-to-failure(MTF) under the stress conditions(here is $V_{use}@85C/140C$ and normal operation conditions. The lifetime criterion is specified as $1_{ppm} \geq 10 \text{ year } @85^{\circ}C$ under normal operation voltage.